

MITOYA MTY-18C LED RING LIGHT



User Manual

Kit contents:

- 1 × MTY-18C lamp
- 1 × Power supply 26 V / 2 A
- 1 × Phone holder with spring clip on flexible arm, ending in ¼ inch male thread
- 1 × Infrared remote control
- 1 × Bag

GEARING UP

- 1) Connect the lamp to the 26 V / 2 A AC adapter included in the kit
- 2) Connect the power adapter to a power outlet
- 3) Turn on the lamp using the [ON/OFF | Dimmer] knob.

Remember the order of connecting the lamp first to the power supply, and then the power supply along with the lamp to the power outlet!

Maintaining the correct sequence will protect the lamp from accidental voltage spikes in the local network that could damage its electronics!

CHANGING LIGHT SETTINGS

The power of the lamp can be adjusted steplessly with the [ON/OFF | Dimmer] knob from 1% to 99%.

The color of the light, i.e. its color temperature, can be adjusted smoothly with the [COLOR TEMPERATURE] knob from 2700 to 6500 K.



MOUNTING THE LAMP ON A TRIPOD 16 mm

The MTY-18C lamp has an integrated, articulated mounting bracket for a 16mm tripod head. The articulation has two butterfly screws. The top screw allows you to change the angle of the lamp. The bottom screw is used to clamp the lamp to the tripod head.

- 1) Remove the bottom screw slightly so that the space in the center of the mounting hole is empty
- 2) Slide the lamp onto the 16mm tripod head
- 3) Tighten the lower screw again until you feel resistance and the lamp is mounted firmly.

ATTENTION!

If you want to mount the lamp on a lighting tripod that has an additional 1-inch thread, make sure that the thread is not protected by a black plastic nut. If the thread is protected by a nut, unscrew and remove it before mounting the lamp - this will ensure greater lamp stability and safe operation.

The MITOYA PENGUIN tripod is the only one that has a horizontally or vertically translating head. If you use the PENGUIN tripod, flip the head to vertical before mounting the lamp!

PHONE HOLDER INSTALLATION

The holder can be mounted inside the circle in one of three dedicated holes. The mount consists of a flexible arm ending in a ball head and a spring-loaded phone clamp. The whole thing is terminated from the bottom with a male ¼ inch thread - screw it into the selected ¼ female hole.

The position of the phone can be further adjusted using the ball head. To change the position of the phone, unscrew the lock ring, change the angle of the holder, and screw the ring back on, locking the holder in the new position.

WARNINGS!

- Do not use a power supply other than the one included in the kit to power the lamp.
- Do not unplug the lamp during operation.
- Do not use the lamp in places with very high temperature and humidity.
- Do not cover the vents in the housing.
- When tilting the lamp forward 90°, always tilt it along one of the tripod legs to maintain a safe center of gravity for the set.

DISTRIBUTION AND CONTACT